TEM0001 Test Board

| 1 Overview | | | |
|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------|-------------------------------------------------------------|--------------------------------------------------|
| 1.1 Key Features | | | |
| 1.2 Revision History | | | |
| OVERVIEWS Release Notes and Know Issues | | | |
| 1.4 Requirements | | | |
| This page describes in detail which software, and the use the module demonstration. Further described is l contained in the Demo Archieve onto the TEM0001. 1.5.1 Download 1.5.2 Design Sources | ir respective versi how to flash the H A brief usage intro | ons, was used to ardware and Soft oduction for each I | generate und ware Design Demo is included. |
| 2 Launch | | | |
| The Hardware Reference Dissipn uses these Smartfu SDRAM Core, Soft SPY Core COM port, Real Time (2.3 Programming Hard and Software | usion 2 SoC, hard Clock and the on-b Designs | Arm® Cortex®-M board LEDs via a | '3 Core, Soft Soft PWM Core. |
| The Software Designs Helle Workersprices Vasora the Hardware Design features to a different regree in features of the Hardware and is very close to the marker and t | ຼື Wm slow_blink ທີ່ອີ່ຮ້າດປູ່ສອງປາຊາດ ຍິດເອຣ ຊາວິນອີບອີບຄິດ "FlashPro Express | and SF2_GNU_S World, which u s | C4_rtc_time use itializes all |
| 3 Hardware Reference Design - Libero | | | |
| 3.1 Smart Design | | | |
| Refer to TEM003-2 Resourcies for the current online v | version of this mar | nual and other ava | ailable |
| documentation. | | | |
| 3.2.2 Clock constrains | | | |
| 4 Software Design - SoftConsole | | | |
| Kov Foatures World | | | |
| 4.1.1 Features | | | |
| 4.1.2 UART Messages Libero 2021.2 (FPG) INFlaction SoftConsole.2021st/Software /DEbum sto | w blick | | |
| UART 4 3 Demo SF2 GNUL SC4 rtc time | w_bunk | | |
| • SDR | | | |
| • 5 Change History and Legal Notices | | | |
| UsebLED accessent Change History | | | |
| Reab Tigge Cleak Notices | | | |
| 5.3 Data Privacy | | | |
| 5.4 Document Warranty | | | |
| Revision History Liability | | | |
| 5.6 Copyright Notice | | | |
| Table of Design Revision Historyenses | | | |
| 5.8 Environmental Protection | | | |
| Date ° 5.9 REACH, RoHS ansottensole | Project Built | Authors | Description |

| Date ° 5. | 9 REACH, RoHS | angoitConsole | Project Built | Authors | Description |
|------------|---------------|---------------|----------------------------------------------------------------------|-------------|-------------------------------------------------------------------------------------|
| 2021-12-15 | 2021.2 | 2021.1 | TEM0001_test- board_Libero- 2021.2 _202112151235 00 .zip | Kilian Jahn | Fixed non critical initial value in Hello World |
| 2021-12-10 | 2021.2 | 2021.1 | TEM0001- test_board- Libero-2021.2 _202112101129 00 .zip | Kilian Jahn | Initial release |

Release Notes and Know Issues

Non known so far.

Requirements

The Designs were created and tested in the following windows environment.

Software

Table of used Software and their Versions

| Software | Version | Note |
|----------------------------------------|--------------|--------------------------------------------------------------------------------------------------------|
| Windows 10 | 21H1 - 19043 | |
| Libero Release | 2021.2 | |
| SoftConsole | 2021.1 | Included in the Libero installation |
| Microsemi Flash Pro 5 module driver | 2.10.0.0 | Utilize onboard programmer and USB / COM port connection. Included in the Libero installation |
| FTDI Driver for the TEM0002 module | 2.12.28.0 | |
| UART / COM-port terminal | | Capturing the modules messages |

Hardware

Design supports following modules:

Table of Hardware Modules

| Module Model | Board Part Short Name | PCB Revision Support | DDR | embedded SI | RAMImbedded Fl | asiNotes |
|----------------------|--------------------------------|----------------------------|------|-------------|----------------|----------|
| TEM0001- 01A-010C | SMF2000 | REV01 | 8 MB | 64 kB | 256 kB | NA |

Additional hardware Requirements:

Table of Additional Hardware

| Additional Hardware | Notes |
|-------------------------------|----------------------------------------------------------------------------------------|
| Demo host computer | Demo was created and tested on windows |
| Micro USB to USB Type A Cable | Power supply, JTAG: Programming the board, UART: Communication Interface to the board. |

Content

The Trenz Electronic Reference Designs and Demos are usable with the specified Microsemi Libero / SoftConsole version. Usage of a different Microsemi Libero / SoftConsole software versions is not recommended.

Download

The download is a ZIP compressed archive, it needs to be extract before usage.

Recommendation :

The path of the extracted archiev is vital for all IDE's, therefore place the extracted archiev outside the user space, e.g. "c:\Extracted_Archieve" [Access rights / Path length limit].

Reference Designs / Demos are available via the following link:

• TEM0001 "Test Board" Reference Design

Design Sources

Content of the zip archive "TEM0001_test-board_Libero-2021.2_20211215123500 .zip" :

Table of Design sources

| Туре | Location | Notes |
|------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Libero | <zip archive=""> / Libero2021.2_Hardware- Design</zip> | Libero Project containing the modules Hardware Reference Design |
| SoftConsole | <zip archive=""> / SoftConsole2021. 1_Workspace_TEM0001 / helloWorld / SF2_GNU_SC4_pwm_ slow_blink / SF2_GNU_SC4_rtc_ti me</zip> | SoftConsole Workspace contains the Software Projects : • Hello World • Blinks a user led • A simple clock |
| SoftConsole | <zip archive=""> / SoftConsole2021. 1_Workspace_TEM0001 / microsemi-cortex-m3. cfg</zip> | File for software debugging in SoftConsole via "Open On Chip Debugger" / OpenOCD |
| FlashPro Express | <zip archive=""> / FlashProExpress2021.2 / RefDes02 / RefDes02-HelloWorld / RefDes02-Zerocitation</zip> | Programming Files to use in FlashPro Express. Omittes the usage of Libero and SoftConsole for Programming. Reference Hardware Design for SoC and periphery Reference Hardware Design + Software Design Hello World Reference Hardware Design for zeroing the eNVM (SoC Flash) |

Launch

Executing a Reference / Demo Design on a module requires the powering of it and a JTAG or UART Connection for Programming and Communication. Often the programming is a two fold process, where the first programming configures the FPGA and the second programming flashes Software code to be executed inside the FPGA / ARM processor.

Connecting

Variant without explicit power connector: Connect the modules Micro-USB to your host pc, this enables the powering of the module and a simultaneous JTAG and UART connection .

Driver check

When the module is connected via USB cable to your demo host computer, in the Windows Device Manager appear the following three board driver related devices:

In section Ports (COM & LPT):

FlashPro5 Port (ComX)

In section Universal Serial Bus controllers:

- USB FP5 Serial Converter A
- USB FP5 Serial Converter B

The Device Manager is accessible via "Right mouse click context menu" from the Windows Start Menu Button. When these devices are not visible, the driver installation through libero could be faulty.

Programming Hard and Software Designs

Before flashing any design to the module, open a terminal programm (e.g. PuTTY or SmarTTY) to the boards COM port, so that when the module restarts after programming, it's messages can be captured.

Programming Variant "IDE"

The Microsemi Hardware and Software Design Tools, Libero and SoftConsole, incorporate the ability to edit, debug and program Hardware and Software Designs. This Programming Variant is for you, when you are interessted in this.

Programming the Hardware design

To program the Hardware Reference Design, start the FPGA Design IDE "Libero SoC v2021.2".



Libero GUI "Run PRGORAMM ACTION"

The Hardware Reference Design can be opened via "Project > Open Project" in the top right corner of Libero (picture above - upper green rectangle). A file dialogue opens, point the dialogue along to the extracted download folder containing the Hardware Design.

Disk :\ Path-to-the-Demo-archive \ Extracted ZIP-archive \ Libero-X.y Hardware-Design\

Double left mouse click onto the project file "TEM0001_RefDesV02.prjx" to open it. The board is automatically selected and setup to be flashed by Libero.

In the upper left section of Libero, select the tab "Design Flow" (picture above - lover green rectangle) and flash it to the board via "Program Design > and double left mouse click onto "Run PROGRAM Action" (picture above - row with blue background).

Warnings should not affect the functionality of a Reference / Demo -Design.

Programming a Software project

Open SoftConsole and press "Browse..." near the right edge. A file dialogue opens, point the dialogue along the extracted download to the folder containing the SoftConsole Workspace.

Disk :\ Path-to-the-Demo-archive \ Extracted ZIP-archive \ SoftConsoleX.y_Workspace_TEM0001 \

Confirm your selection by pressing "Ok" , the dialogue closes, and open The SoftConsole by pressing "Launch" $\ensuremath{\mathsf{Launch}}$





Subsequently the program opens and shows the software project's who are contained inside the workspace to the left, under "Project Explorer".



SoftConsole GUI

To simply run a Project, press the triangle right to the button marked with a "R" in the picture above and select a variant of the demo.

Pressing the triangle next to the button marked with "D" let you select which variant to be executed in debug mode.

Debug controls - Resume - Pause - Stop

SoftConsole "Debug controlls"

Switch between Debug and Code Writting perspective (upper right corner program window)



SoftConsole "Switch GUI layout"

Programming or Debugging a Software Design with the IDE SoftConsole needs to be manually stopped, in order to rerun it or to alter to a different Design.

Programming Variant "FlashPro Express"

When you just want to run a SoC Design, this is for you.

To program a Hardware and Software Design simultaneously, open FlashPro Express. Via left click onto Open in the section "Job Projects" open a file dialogue. Point to

Disk :\ Path-to-the-Demo-archive \ Extracted ZIP-archive \ FlashProExpressX.Y \ Desired Demo \ JobFile . pro

| ningt View Tools Help | Path\FlashProExpre | ss\Demo\JobFile.pro |
|----------------------------|--------------------|---------------------------|
| Refresh/Rescan Programmers | [| |
| Prog | rammer | 🚹 M2S010 🕮 Ф ТВО ТВІ Ф |
| 1 🕑 🗹 🎉 200A26130 | IDLE | IDLE |
| | | |
| PROGRAM | • | |
| PROGRAM RUN | • | |
| RUN | • | |
| PROGRAM RUN | arnings 🜒 Info | |

FlashPro Express GUI

To program the Design, press Run.

Hardware Reference Design - Libero





Constrains

IO constraints

SoC_Dedicated.pdc

```
# Microsemi I/O Physical Design Constraints file
# User I/O Constraints file
# Version: v2021.1 2021.1.0.17
# Family: SmartFusion2 , Die: M2S010 , Package: 400 VF
# Date generated: Fri Aug 13 07:56:00 2021
#
# User Locked I/O Bank Settings
#
#
# Unlocked I/O Bank Settings
# The I/O Bank Settings can be locked by directly editing this file
# or by making changes in the I/O Attribute Editor
#
#
# User Locked I/O settings
#
#
# Dedicated Peripheral I/O Settings
#
set_io CLK1
                       \
   -pinname N16
                       \backslash
    -fixed yes
                       \
    -DIRECTION INPUT
#
# Unlocked I/O settings
# The I/Os in this section are unplaced or placed but are not locked
# the other listed attributes have been applied
#
#
#Ports using Dedicated Pins
#
set_io DEVRST_N
                       \backslash
   -pinname U17
                       \backslash
    -DIRECTION INPUT
set_io XTL
   -pinname Y18
                       -DIRECTION INPUT
```

SDRAM.pdc

```
# Microsemi I/O Physical Design Constraints file
# User I/O Constraints file
# Version: v11.8 11.8.0.26
# Family: SmartFusion2 , Die: M2S010 , Package: 400 VF
# Date generated: Fri Oct 20 14:01:01 2017
#
# User Locked I/O Bank Settings
#
#
# Unlocked I/O Bank Settings
# The I/O Bank Settings can be locked by directly editing this file
# or by making changes in the I/O Attribute Editor
#
#
# User Locked I/O settings
#
set_io {BA[0]}
                         \setminus
   -pinname W10
                         \backslash
    -fixed yes
                         \backslash
    -DIRECTION OUTPUT
set_io {BA[1]}
   -pinname V12
                         \mathbf{1}
    -fixed yes
                         \backslash
    -DIRECTION OUTPUT
set_io CAS_N
                         \
   -pinname Y12
                         \backslash
    -fixed yes
                         \setminus
    -DIRECTION OUTPUT
set_io CKE
                         \
   -pinname Y13
                         \backslash
   -fixed yes
                         \backslash
    -DIRECTION OUTPUT
set_io {CS_N[0]}
                         \
   -pinname R13
                         \backslash
    -fixed yes
                         \backslash
    -DIRECTION OUTPUT
```

set_io {DQ[0]} / -pinname Fl \ -fixed yes / -DIRECTION INOUT set_io {DQ[1]} / -pinname Gl / -fixed yes \ -DIRECTION INOUT set_io {DQ[2]} \ -pinname E2 -fixed yes -DIRECTION INOUT set_io {DQ[3]} \ -pinname G2 / -fixed yes \ -DIRECTION INOUT set_io {DQ[4]} -pinname E3 \ -fixed yes \ -DIRECTION INOUT set_io {DQ[5]} -pinname G3 \ -fixed yes / -DIRECTION INOUT \setminus set_io {DQ[6]} -pinname F3 / -fixed yes / -DIRECTION INOUT set_io {DQ[7]} \ -pinname F4 \ -fixed yes \backslash -DIRECTION INOUT set_io {DQ[8]} \ -pinname J7 \ -fixed yes \backslash -DIRECTION INOUT set_io {DQ[9]} \backslash

```
-pinname G6
                        /
    -fixed yes
                       \backslash
    -DIRECTION INOUT
set_io {DQ[10]}
                        \
    -pinname F6
                        \
    -fixed yes
    -DIRECTION INOUT
set_io {DQ[11]}
                        \
   -pinname H5
                        /
    -fixed yes
                        \
    -DIRECTION INOUT
set_io {DQ[12]}
    -pinname H6
                        \
    -fixed yes
                        \
    -DIRECTION INOUT
set_io {DQ[13]}
   -pinname H4
                        \
    -fixed yes
                        /
    -DIRECTION INOUT
set_io {DQ[14]}
                       \backslash
    -pinname F5
                        /
    -fixed yes
                        \
    -DIRECTION INOUT
set_io {DQ[15]}
                        \
    -pinname G4
                        \
    -fixed yes
                        \
    -DIRECTION INOUT
set_io {DQM[0]}
   -pinname E5
    -fixed yes
    -DIRECTION OUTPUT
set_io {DQM[1]}
   -pinname F7
    -fixed yes
    -DIRECTION OUTPUT
set_io RAS_N
                        \backslash
```

```
-fixed yes
                       \backslash
    -DIRECTION OUTPUT
set_io {SA[0]}
                       -pinname Ull
                       \
    -fixed yes
    -DIRECTION OUTPUT
set_io {SA[1]}
   -pinname U12
    -fixed yes
    -DIRECTION OUTPUT
set_io {SA[2]}
   -pinname V11
   -fixed yes
    -DIRECTION OUTPUT
set_io {SA[3]}
   -pinname Y10
    -fixed yes
                       /
    -DIRECTION OUTPUT
set_io {SA[4]}
    -pinname W15
    -fixed yes
                       /
    -DIRECTION OUTPUT
set_io {SA[5]}
   -pinname U14
    -fixed yes
                       \
   -DIRECTION OUTPUT
set_io {SA[6]}
   -pinname Y15
    -fixed yes
    -DIRECTION OUTPUT
set_io {SA[7]}
   -pinname W14
    -fixed yes
   -DIRECTION OUTPUT
set_io {SA[8]}
    -pinname T15
                       \
    -fixed yes
                       \
    -DIRECTION OUTPUT
```

-pinname U13

set_io {SA[9]} \ -pinname W13 \ -fixed yes \ -DIRECTION OUTPUT set_io {SA[10]} -pinname T13 / -fixed yes -DIRECTION OUTPUT set_io {SA[11]} -pinname V14 \ -fixed yes \ -DIRECTION OUTPUT set_io {SA[12]} -pinname V15 \ -fixed yes / -DIRECTION OUTPUT set_io {SA[13]} -pinname Y16 -fixed yes \ -DIRECTION OUTPUT set_io WE_N -pinname R12 -fixed yes \ -DIRECTION OUTPUT set_io SDRCLK_OUT -pinname T14 \ -fixed yes \ -DIRECTION OUTPUT

SPI.pdc

```
# Microsemi I/O Physical Design Constraints file
# User I/O Constraints file
# Version: v2021.1 2021.1.0.17
# Family: SmartFusion2 , Die: M2S010 , Package: 400 VF
# Date generated: Sat Jul 24 11:29:36 2021
#
# User Locked I/O Bank Settings
#
#
# Unlocked I/O Bank Settings
# The I/O Bank Settings can be locked by directly editing this file
# or by making changes in the I/O Attribute Editor
#
#
# User Locked I/O settings
#
set_io SPISCLKO
                         \backslash
   -pinname P18
                         \backslash
    -fixed yes
                         \backslash
    -DIRECTION OUTPUT
set_io SPISDI
   -pinname K16
                        \backslash
    -fixed yes
                        \mathbf{1}
    -DIRECTION INPUT
set_io SPISDO
                         \backslash
   -pinname P19
                         \backslash
    -fixed yes
                         \setminus
    -DIRECTION OUTPUT
set_io SPISS
                         \backslash
   -pinname K15
                         \setminus
   -fixed yes
                         \backslash
   -DIRECTION OUTPUT
```

```
LEDs_Button.pdc
# SMF2000 Board Pinout, 2018-11-27
# LED1-LED8
set_io {PWM[0]} -pinname E18 -fixed yes -iostd LVCMOS33 -OUT_DRIVE 16
set_io {PWM[1]} -pinname R17 -fixed yes -iostd LVCMOS33 -OUT_DRIVE 16
set_io {PWM[2]} -pinname R18 -fixed yes -iostd LVCMOS33 -OUT_DRIVE 16
set_io {PWM[3]} -pinname T18 -fixed yes -iostd LVCMOS33 -OUT_DRIVE 16
set_io {PWM[4]} -pinname R16 -fixed yes -iostd LVCMOS33 -OUT_DRIVE 16
set_io {PWM[5]} -pinname R16 -fixed yes -iostd LVCMOS33 -OUT_DRIVE 16
set_io {PWM[6]} -pinname E1 -fixed yes -iostd LVCMOS33 -OUT_DRIVE 16
set_io {PWM[7]} -pinname D2 -fixed yes -iostd LVCMOS33 -OUT_DRIVE 16
#USER_LED
set_io {USER_LED} -pinname G17 -fixed yes -iostd LVCMOS33 -DIRECTION OUTPUT
# USER_BTN
set_io taster -pinname B19 -fixed yes -iostd LVCMOS33 -RES_PULL Up
```

Clock constrains

```
user_clock_constraints.sdc

create_clock -name {FCCC_C0_0_FCCC_C0_0_GL0_net} -period 10 -waveform {0
5 } [ get_nets { FCCC_C0_0/FCCC_C0_0/GL0_net } ]
create_clock -name {FCCC_C1_0_GL0_net} -period 250 -waveform {0 125 } [
get_nets { FCCC_C1_0/FCCC_C1_0/GL0_net } ]
create_clock -name {XTL} -period 83.3333 -waveform {0 41.6667 } [
get_ports { XTL } ]
create_clock -name {OSC_C0_0_OSC_C0_0_RCOSC_25_50MHZ_02F} -period 20 -
waveform {0 10 } [ get_pins { FCCC_C0_0/FCCC_C0_0/CCC_INST/RCOSC_25_50MHZ
} ]
create_clock -name {CLK1} -period 83.3333 -waveform {0 41.6667 } [
get_ports { CLK1 } ]
```

Software Design - SoftConsole

Software Designs contained insode the workspace.

Hello World

The Hello World utializes all features of the Hardware. It runs an endless loop, which interacts with the modules periphy in each loop. It is very close to the modules production test.

Features

- Display the system time since power up
- Identifies SPI Flash IDs
- Tests different ~5 % of the SDR cells each loop and tracks the result above all loops
- Illuminates the 8 user LEDs in a row in selectable patterns [Counter, running & bouncing light]
- Illuminates all user LEDs while the user button is pressed

UART Messages

Hello World loop message

Interaction

• Press the User Button S2 to switch the illumination patterns

Demo SF2_GNU_SC4_pwm_slow_blink

This software design illuminates the User LED D10. The User LED D2 transitions between illuminated and off continuously.

Demo SF2_GNU_SC4_rtc_time

Resambles a clock with time and date. Time and Date can be set.

| RTC time Initialization message |
|-------------------------------------------------------------------------------------------|
| ****************** |
| ************* SmartFusion2 RTC Calendar Time Example ************************************ |
| ************************* |
| This example project reads the time from the SmartFusion2 RTC. |
| A simple command line interface allows the following operations: |
| - Set the RTC time by pressing "t" |
| - Set the RTC date by pressing "d" |
| |
| |
| Saturday January 1 2000 (week 1) 00:00:34 |

Interaction

To edit the time press t or d for the date, confirm via Enter. The program alters to setup mode. Changing the values for hour, minute and second is done independently for each value, enter a valid value and press Enter. When all values are entered, the new values are accepted. A non valid value will terminate the setup mode.

Appx. A: Change History and Legal Notices

Document Change History

To get content of older revision got to "Change History" of this page and select older document revision number.

| Date | Document Revision | Authors | Description |
|------|-------------------|---------|--------------------------|
| | | | Libero 2021.2 release |
| | | | |

| Error | Error | Error |
|------------|------------|------------|
| renderi | renderi | renderi |
| ng | ng | ng |
| macro | macro | macro |
| 'page- | 'page- | 'page- |
| info' | info' | info' |
| Amhimun | Amhinun | Amhiana |
| Ambiguo | Ambiguo | Ambiguo |
| us | us | us |
| metriod | everleed | nietriod |
| overload | overload | overload |
| ing for | ing for | ing for |
| interiod | inte | method |
| јак. | јак. | jak. |
| proxy27 | proxy27 | proxy27 |
| 9.\$Proxy | 9.\$Proxy | 9.\$Proxy |
| 4022#ha | 4022#ha | 4022#ha |
| sConten | sConten | sConten |
| tLevelPe | tLevelPe | tLevelPe |
| rmission | rmission | rmission |
| • | | · |
| Cannot | Cannot | Cannot |
| resolve | resolve | resolve |
| which | which | which |
| method | method | method |
| to | to | to |
| invoke | invoke | invoke |
| for [null, | for [null, | for [null, |
| class | class | class |
| java. | java. | java. |
| lang. | lang. | lang. |
| String, | String, | String, |
| class | class | class |
| com. | com. | com. |
| atlassian | atlassian | atlassian |
| | | |
| confluen | confluen | confluen |
| ce. | ce. | ce. |
| pages. | pages. | pages. |
| Page] | Page] | Page] |
| 111 | 111 | 11 |

| due to | due to | due to |
|-----------|-----------|-----------|
| overlapp | overlapp | overlapp |
| ing | ing | ing |
| prototyp | prototyp | prototyp |
| es | es | es |
| between | between | between |
| : | : | : |
| [interfac | [interfac | [interfac |
| e com. | e com. | e com. |
| atlassian | atlassian | atlassian |
| | | |
| confluen | confluen | confluen |
| ce.user. | ce.user. | ce.user. |
| Conflue | Conflue | Conflue |
| nceUser | nceUser | nceUser |
| , class | , class | , class |
| java. | java. | java. |
| lang. | lang. | lang. |
| String, | String, | String, |
| class | class | class |
| com. | com. | com. |
| atlassian | atlassian | atlassian |
| | | |
| confluen | confluen | confluen |
| ce.core. | ce.core. | ce.core. |
| Content | Content | Content |
| EntityOb | EntityOb | EntityOb |
| ject] | ject] | ject] |
| [interfac | [interfac | [interfac |
| e com. | e com. | e com. |
| atlassian | atlassian | atlassian |
| .user. | .user. | .user. |
| User, | User, | User, |
| class | class | class |
| java. | java. | java. |
| lang. | lang. | lang. |
| String, | String, | String, |
| class | class | class |
| com. | com. | com. |
| | | |

| atlassian | atlassian | atlassian | |
|-----------|-----------|------------|---|
| | | | |
| confluen | confluen | confluen | |
| ce.core. | ce.core. | ce.core. | |
| Content | Content | Content | |
| EntityOb | EntityOb | EntityOb | |
| ject] | ject] | ject] | |
| | | | |
| | | | |
| | all | | |
| | | | |
| | | Error | |
| | | renderi | |
| | | ng | |
| | | macro | |
| | | 'page- | |
| | | info' | |
| | | Ambiguo | |
| | | us | |
| | | method | |
| | | overload | |
| | | ing for | |
| | | method | |
| | | jdk. | |
| | | proxy27 | |
| | | 9.\$Proxy | |
| | | 4022#ha | |
| | | sConten | |
| | | tLevelPe | |
| | | rmission | |
| | | | |
| | | Cannot | |
| | | resolve | |
| | | which | |
| | | method | |
| | | to | |
| | | invoke | |
| | | for [null, | |
| | | class | |
| | I | 1 | 1 |

java. lang. String, class com. atlassian confluen ce. pages. Page] due to overlapp ing prototyp es between [interfac e com. atlassian confluen ce.user. Conflue nceUser , class java. lang. String, class com. atlassian confluen ce.core. Content EntityOb ject]



Document change history.

Legal Notices

Data Privacy

Please also note our data protection declaration at https://www.trenz-electronic.de/en/Data-protection-Privacy

Document Warranty

The material contained in this document is provided "as is" and is subject to being changed at any time without notice. Trenz Electronic does not warrant the accuracy and completeness of the materials in this document. Further, to the maximum extent permitted by applicable law, Trenz Electronic disclaims all warranties, either express or implied, with regard to this document and any information contained herein, including but not limited to the implied warranties of merchantability, fitness for a particular purpose or non infringement of intellectual property. Trenz Electronic shall not be liable for errors or for incidental or consequential damages in connection with the furnishing, use, or performance of this document or of any information contained herein.

Limitation of Liability

In no event will Trenz Electronic, its suppliers, or other third parties mentioned in this document be liable for any damages whatsoever (including, without limitation, those resulting from lost profits, lost data or business interruption) arising out of the use, inability to use, or the results of use of this document, any documents linked to this document, or the materials or information contained at any or all such documents. If your use of the materials or information from this document results in the need for servicing, repair or correction of equipment or data, you assume all costs thereof.

Copyright Notice

No part of this manual may be reproduced in any form or by any means (including electronic storage and retrieval or translation into a foreign language) without prior agreement and written consent from Trenz Electronic.

Technology Licenses

The hardware / firmware / software described in this document are furnished under a license and may be used /modified / copied only in accordance with the terms of such license.

Environmental Protection

To confront directly with the responsibility toward the environment, the global community and eventually also oneself. Such a resolution should be integral part not only of everybody's life. Also enterprises shall be conscious of their social responsibility and contribute to the preservation of our common living space. That is why Trenz Electronic invests in the protection of our Environment.

REACH, RoHS and WEEE

REACH

Trenz Electronic is a manufacturer and a distributor of electronic products. It is therefore a so called downstream user in the sense of REACH. The products we supply to you are solely non-chemical products (goods). Moreover and under normal and reasonably foreseeable circumstances of application, the goods supplied to you shall not release any substance. For that, Trenz Electronic is obliged to neither register nor to provide safety data sheet. According to present knowledge and to best of our knowledge, no SVHC (Substances of Very High Concern) on the Candidate List are contained in our products. Furthermore, we will immediately and unsolicited inform our customers in compliance with REACH - Article 33 if any substance present in our goods (above a concentration of 0,1 % weight by weight) will be classified as SVHC by the European Chemicals Agency (ECHA).

RoHS

Trenz Electronic GmbH herewith declares that all its products are developed, manufactured and distributed RoHS compliant.

WEEE

Information for users within the European Union in accordance with Directive 2002/96/EC of the European Parliament and of the Council of 27 January 2003 on waste electrical and electronic equipment (WEEE).

Users of electrical and electronic equipment in private households are required not to dispose of waste electrical and electronic equipment as unsorted municipal waste and to collect such waste electrical and electronic equipment separately. By the 13 August 2005, Member States shall have ensured that systems are set up allowing final holders and distributors to return waste electrical and electronic equipment at least free of charge. Member States shall ensure the availability and accessibility of the necessary collection facilities. Separate collection is the precondition to ensure specific treatment and recycling of waste electrical and electronic equipment and is necessary to achieve the chosen level of protection of human health and the environment in the European Union. Consumers have to actively contribute to the success of such collection and the return of waste electrical and electronic equipment. Presence of hazardous substances in electrical and electronic equipment results in potential effects on the environment and human health. The symbol consisting of the crossed-out wheeled bin indicates separate collection for waste electrical and electronic equipment.

Trenz Electronic is registered under WEEE-Reg.-Nr. DE97922676.

Error rendering macro 'page-info'

Ambiguous method overloading for method jdk. proxy279.\$Proxy4022#hasContentLevelPermission. Cannot resolve which method to invoke for [null, class java.lang.String, class com.atlassian.confluence.pages.Page] due to overlapping prototypes between: [interface com.atlassian.confluence.user. ConfluenceUser, class java.lang.String, class com.atlassian.confluence.core. ContentEntityObject] [interface com.atlassian.user.User, class java.lang.String, class com.atlassian.confluence.core.ContentEntityObject]