

TE0710 CPLD

Table of contents

Overview

- 1 Overview

Firmware for PCB CPLD with designator **U4**. CPLD Device in Chain: LCMX02-256HC

1.1 Feature Summary

- 1.2 Firmware Revision and supported PCB Revision

- 2 Product Specification

Feature Summary

- 2.1 Functional Description

- 2.2 Functional Description

- JTAG routing
- Reset
- LED sequencing
- USER IO
- I2C Interface
- 2.2.1 JTAG
- 2.2.2 Reset
- 2.2.3 Power
- 2.2.4 USER IO
- 2.2.5 USER IO
- 2.2.6 LED
- 2.2.7 I2C Interface

- 3 Appx. A: Change History and Legal Notices

Firmware Revision and supported PCB Revision

- 3.1 Revision Changes

- 3.2 Document Change History

See Document Change History

- 3.3 Legal Notices

- 3.4 Data Privacy

- 3.5 Document Warranty

- 3.6 Limitation of Liability

- 3.7 Copyright Notice

- 3.8 Technology Licenses

- 3.9 Environmental Protection

- 3.10 PEACH, RoHS and WEEE

Product Specification

Port Description

- 4 Table of contents

Name	Direction	Pin	Pullup/down	Bank Power	Description
DONE	in	13	UP	LVC MOS33	FPGA DONE signal
EN1	in	16	UP	LVC MOS33	B2B Enable Pin - low active
F_TCK	out	28	-	LVC MOS33	JTAG FPGA
F_TDI	out	27	-	LVC MOS33	JTAG FPGA
F_TDO	in	23	-	LVC MOS33	JTAG FPGA
F_TMS	out	25	-	LVC MOS33	JTAG FPGA
JTAGSEL	in	26	NONE	LVC MOS33	Enable JTAG access to CPLD for Firmware update (zero: JTAG routed to module, one: CPLD access)
BOOTMODE	in	11	UP	LVC MOS33	B2B Boot Mode Pin
NOSEQ	in	12	UP	LVC MOS33	B2B NOSEQ Pin
PG_ALL	in	10	UP	LVC MOS33	Power good - low active, from power monitor U23
PGOOD	out	14	UP	LVC MOS33	B2B PGOOD
PROG_B	out	17	UP	LVC MOS33	FPGA PROG_B Reset

SC_nRST	in	8	UP	LVC MOS33	B2B Reset - low active
SYSLED1	out	9	NONE	LVC MOS33	Green LED D2
SYSLED2	out	5	NONE	LVC MOS33	Red LED D1
TCK	in	30	NONE	LVC MOS33	JTAG B2B
TDI	in	32	DOWN	LVC MOS33	JTAG B2B
TDO	out	1	NONE	LVC MOS33	JTAG B2B
TMS	in	29	DOWN	LVC MOS33	JTAG B2B
ULI_2	out	20	UP	LVC MOS15	FPGA Bank 35 Pin J5 - I2C CLOCK Pin to FPGA
ULI_CPLD	out	4	NONE	LVC MOS33	J1 (Ultra Small Surface Mount Coax)
ULI_SYSTEM	in	21	UP	LVC MOS15	FPGA Bank 35 Pin G3 - I2C DATA Pin to FPGA or input for UFL

Functional Description

JTAG

JTAG signals routed directly through the CPLD to FPGA. Access between CPLD and FPGA can be multiplexed via *JTAGEN* (logical one for CPLD, logical zero for FPGA) on JM1-89.

Reset

PROG_B is triggered by *SC_nRST* or *PG_ALL* or *EN1* after power on delay.

Power

PGOOD is '0' when *PG_ALL* or *EN1* is '0', else high impedance.

USER IO

Various signals are connected to an I2C register.

I2C GPIO_input register Bit 15 down to Bit 9 contain *SC_nRST*, *BOOTMODE*, *PGOOD*, *EN1*, *DONE*, *PG_ALL* and *NOS EQ*.

Their state can be read from FPGA side over I2C.

ULI_SYSTEM serves as the I2C data pin but is also connected to *ULI_CPLD*.


USER IO


MODE_SC1 is connected to a I2C Register bit. GPIO_input(18). Its state can be read from FPGA side over I2C.

UIO is connected to *UFL* but also serves as the I2C data pin.

LED

RED LED D1 (SYSLED2) shows a certain blinking pattern in case one of the status signals is active, otherwise it can be controlled via I2C from FPGA side or is simply OFF.

Blink sequence	Priority	Condition	Description
***** 	highest	SC_nRST= LOW (low active)	external reset from carrier is pressed
*****0			blink sequence not used
*****00			blink sequence not used
*****000		PG_ALL is zero	One of the power rails of the internal Voltages DCDCs is down
***0000		EN1 is zero	B2B enable Pin is active (low active), coming from the carrier
***00000			blink sequence not used
**000000			blink sequence not used

*0000000		DONE = '0'	FPGA not programmed. No design on QSPI Flash?
continuously ON	lowest	software controlled command via I2C Interface. LED = GPIO_output(1) when GPIO_output(0) = 0	Set bit GPIO_output(0) LOW to control the LED with GPIO_output(1).
continuously OFF			If none of the above condition is met

GREEN LED D2 (SYSLED1) software controlled command via I2C Interface or is simply OFF.

Blink sequence	Condition	Description
continuously ON	software controlled command via I2C Interface. LED = GPIO_output(3) when GPIO_output(2) = 0	Set bit GPIO_output(2) LOW to control the LED with GPIO_output(3).
continuously OFF		If none of the above condition is met

I2C Interface

This subsystem provides 2 x 32-bit (segmented in eight 8-bit) of general purpose parallel input and output (I/O) expansion for the I2C bus protocol. Address of this I2C device is 0x20. This module contains eight 8-bit registers for reading and writing (GPIO_input[7:0] to GPIO_input[31:24] and GPIO_output[7:0] to GPIO_output[31:24]) separately with address 0x00 to 0x03. These registers can be accessed with I2C commands on a standalone application or, more simply, from petalinux running on the Microblaze. Refer to TE0710 reference design (test board).

```

root@petalinux:~# i2cdetect -l
i2c-0 i2c          xliic-i2c 40800000.i2c          I2C
adapter
root@petalinux:~# i2cget -y 0 0x20 0x00
0x03
root@petalinux:~# i2cget -y 0 0x20 0x01
0xfe
root@petalinux:~# i2cget -y 0 0x20 0x02
0x01
root@petalinux:~# i2cget -y 0 0x20 0x03
0x0a
root@petalinux:~# i2cset -y 0 0x20 0x00 0x0a

```

Four registers can be read and four can be written.

GPIO_input(7 downto 0)	readable	0x00	contains the CPLD Firmware Revision (not the PCB revision)
GPIO_input(15 downto 8)	readable	0x01	SC_nRST, BOOTMODE, PGOOD, EN1, DONE, PG_ALL, NOSEQ, '0'
GPIO_input(23 downto 16)	readable	0x02	contains: NOSEQ state in bit 16.
GPIO_input(31 downto 24)	readable	0x03	empty
GPIO_output(7 downto 0)	writable	0x00	Bit 1 to 3 are mapped to SYSLED1 and SYSLED2. Write '1' to Bit 1 and Bit 3 to turn on the LED D1 and D2.
GPIO_output(15 downto 8)	writable	0x01	not mapped
GPIO_output(23 downto 16)	writable	0x02	Bit 16 is mapped to NOSEQ if no reset occurs
GPIO_output(31 downto 24)	writable	0x03	not mapped

Appx. A: Change History and Legal Notices

Revision Changes

changes Firmware REV02(old version) to REV03:

- Signals are renamed according to the schematic.
- NOSEQ pin is added.
- LED function changed. New blinking pattern for critical signal states
- I2C to GPIO slave added
- SC_nRST, BOOTMODE, PGOOD, EN1, DONE, PG_ALL, NOSEQ signals can be read from I2C
- CPLD_REVISION as generic parameter added
- NOSEQ defined as INOUT
- ULI_SYSTEM and ULI_2 pins defined as I2C pins. Added PullUps for I2C. ULI_SYSTEM is still also connected to ULI_CPLD

Document Change History

To get content of older revision got to "Change History" of this page and select older document revision number.

Date	Document Revision	CPLD Firmware Revision	Supported PCB Revision	Authors	Description	Firmware Release
------	-------------------	------------------------	------------------------	---------	-------------	------------------

		REV03	REV03		- REV02, Firmware released 2024-02-15 - SC-PGM-TE0710-03_SC0710-03_2024021	SC-PGM-TE0710-03_SC0710-03_2024021
					- REV02, Firmware released 2024-02-15 - SC-PGM-TE0710-03_SC0710-03_2024021	SC-PGM-TE0710-03_SC0710-03_2024021
					- REV02, Firmware released 2024-02-15 - SC-PGM-TE0710-03_SC0710-03_2024021	SC-PGM-TE0710-03_SC0710-03_2024021
					- REV02, Firmware released 2024-02-15 - SC-PGM-TE0710-03_SC0710-03_2024021	SC-PGM-TE0710-03_SC0710-03_2024021
22 Sept 2022	v.5	REV01	REV02	John Hartfiel	- some typo - Newer Preliminary CPLD version with some bugfixes for TE0706 usage: Design Note 20210519 TE0710-02 CPLD Firmware	
23 Mar 2018	v.3	REV01	REV02	John Hartfiel	REV01 , Firmware released 2015-04-17	
2018-03-21	v.1	REV01	REV02		Initial release	
					Initial release	
					Initial release	
	All				Initial release	

Legal Notices

Data Privacy

Please also note our data protection declaration at <https://www.trenz-electronic.de/en/Data-protection-Privacy>

Document Warranty

The material contained in this document is provided "as is" and is subject to being changed at any time without notice. Trenz Electronic does not warrant the accuracy and completeness of the materials in this document. Further, to the maximum extent permitted by applicable law, Trenz Electronic disclaims all warranties, either express or implied, with regard to this document and any information contained herein, including but not limited to the implied warranties of merchantability, fitness for a particular purpose or non infringement of intellectual property. Trenz Electronic shall not be liable for errors or for incidental or consequential damages in connection with the furnishing, use, or performance of this document or of any information contained herein.

Limitation of Liability

In no event will Trenz Electronic, its suppliers, or other third parties mentioned in this document be liable for any damages whatsoever (including, without limitation, those resulting from lost profits, lost data or business interruption) arising out of the use, inability to use, or the results of use of this document, any documents linked to this document, or the materials or information contained at any or all such documents. If your use of the materials or information from this document results in the need for servicing, repair or correction of equipment or data, you assume all costs thereof.

Copyright Notice

No part of this manual may be reproduced in any form or by any means (including electronic storage and retrieval or translation into a foreign language) without prior agreement and written consent from Trenz Electronic.

Technology Licenses

The hardware / firmware / software described in this document are furnished under a license and may be used /modified / copied only in accordance with the terms of such license.

Environmental Protection

To confront directly with the responsibility toward the environment, the global community and eventually also oneself. Such a resolution should be integral part not only of everybody's life. Also enterprises shall be conscious of their social responsibility and contribute to the preservation of our common living space. That is why Trenz Electronic invests in the protection of our Environment.

REACH, RoHS and WEEE

REACH

Trenz Electronic is a manufacturer and a distributor of electronic products. It is therefore a so called downstream user in the sense of [REACH](#). The products we supply to you are solely non-chemical products (goods). Moreover and under normal and reasonably foreseeable circumstances of application, the goods supplied to you shall not release any substance. For that, Trenz Electronic is obliged to neither register nor to provide safety data sheet. According to present knowledge and to best of our knowledge, no [SVHC \(Substances of Very High Concern\) on the Candidate List](#) are contained in our products. Furthermore, we will immediately and unsolicited inform our customers in compliance with REACH - Article 33 if any substance present in our goods (above a concentration of 0,1 % weight by weight) will be classified as SVHC by the [European Chemicals Agency \(ECHA\)](#).

RoHS

Trenz Electronic GmbH herewith declares that all its products are developed, manufactured and distributed RoHS compliant.

WEEE

Information for users within the European Union in accordance with Directive 2002/96/EC of the European Parliament and of the Council of 27 January 2003 on waste electrical and electronic equipment (WEEE).

Users of electrical and electronic equipment in private households are required not to dispose of waste electrical and electronic equipment as unsorted municipal waste and to collect such waste electrical and electronic equipment separately. By the 13 August 2005, Member States shall have ensured that systems are set up allowing final holders and distributors to return waste electrical and electronic equipment at least free of charge. Member States shall ensure the availability and accessibility of the necessary collection facilities. Separate collection is the precondition to ensure specific treatment and recycling of waste electrical and electronic equipment and is necessary to achieve the chosen level of protection of human health and the environment in the European Union. Consumers have to actively contribute to the success of such collection and the return of waste electrical and electronic equipment. Presence of hazardous substances in electrical and electronic equipment results in potential effects on the environment and human health. The symbol consisting of the crossed-out wheeled bin indicates separate collection for waste electrical and electronic equipment.

Trenz Electronic is registered under WEEE-Reg.-Nr. DE97922676.

Error rendering macro 'page-info'

Ambiguous method overloading for method `jdk.proxy241.$Proxy3496#hasContentLevelPermission`.
Cannot resolve which method to invoke for `[null, class java.lang.String, class com.atlassian.confluence.pages.Page]` due to overlapping prototypes between: `[interface com.atlassian.confluence.user.ConfluenceUser, class java.lang.String, class com.atlassian.confluence.core.ContentEntityObject]`
`[interface com.atlassian.user.User, class java.lang.String, class com.atlassian.confluence.core.ContentEntityObject]`