

TE0841 CPLD

Table of contents

- 1 [Table of contents](#)
- 2 [Overview](#)
 - 2.1 [Feature Summary](#)
 - 2.2 [Firmware Revision and supported PCB Revision](#)
- 3 [Product Specification](#)
 - 3.1 [Port Description](#)
 - 3.2 [Functional Description](#)
 - 3.2.1 [JTAG](#)
 - 3.2.2 [Power](#)
 - 3.2.3 [Reset](#)
 - 3.2.4 [PUD_C](#)
 - 3.2.5 [LED](#)
- 4 [Appx. A: Change History and Legal Notices](#)
 - 4.1 [Revision Changes](#)
 - 4.2 [Document Change History](#)
 - 4.3 [Legal Notices](#)
 - 4.4 [Data Privacy](#)
 - 4.5 [Document Warranty](#)
 - 4.6 [Limitation of Liability](#)
 - 4.7 [Copyright Notice](#)
 - 4.8 [Technology Licenses](#)
 - 4.9 [Environmental Protection](#)
 - 4.10 [REACH, RoHS and WEEE](#)

Overview

Firmware for PCB CPLD with designator U18. CPLD Device in Chain: LCMX02-256HC

Feature Summary

- Reset Management
- JTAG
- Power Management
- PUD_C
- LED

Firmware Revision and supported PCB Revision

See Document Change History

Product Specification

Port Description

Name / opt. VHD Name	Direction	Pin	Bank Power	Description
CPLD_IO / XIO	in	17	1.8V	FPGA Bank 45 P28

DONE	in	13	1.8V	FPGA Configuration DONE_0 Pin
EN_PL	out	20	3.3V	Enable module power
F_TCK / C_TCK	out	8	1.8V	JTAG to FPGA
F_TDI / C_TDI	out	10	1.8V	JTAG to FPGA
F_TDO / C_TDO	in	11	1.8V	JTAG to FPGA
F_TMS / C_TMS	out	9	1.8V	JTAG to FPGA
INIT_B	in	16	1.8V	FPGA INIT_B
JTAGMODE	in	26	3.3V	Enable JTAG access to CPLD for Firmware update (zero: JTAG routed to FPGA, one: CPLD access)
/ LED1	out	4	3.3V	green LED D1
N.C. / dummy	out	5	3.3V	dummy pin
nRST_SC0 / RESIN	in	21	3.3V	B2B Reset_N
PROG_B	out	12	1.8V	FPGA Configuration PROGRAM_B_0 Pin
PUDC_B	out	14	1.8V	FPGA PUDC_B
SC1		23	3.3V	B2B JM1-32 / 4x5 Boot MODE Pin / currently_not_used
SC2	inout	25	3.3V	B2B JM1-30 / 4x5 PGOOD Pin
SC3	in	27	3.3V	B2B JM1-28 / 4x5 Power Enable Pin
SC4		28	3.3V	B2B JM1-7 / 4x5 No Sequencing Pin / currently_not_used
TCK / M_TCK	in	30	3.3V	JTAG from B2B connector
TDI / M_TDI	in	32	3.3V	JTAG from B2B connector
TDO / M_TDO	out	1	3.3V	JTAG from B2B connector
TMS / M_TMS	in	29	3.3V	JTAG from B2B connector

Functional Description

JTAG

JTAG signals routed directly through the CPLD to FPGA. Access between CPLD and FPGA can be multiplexed via JTAGEN (logical one for CPLD, logical zero for FPGA).

Power

EN_PL is set constant one.

SC2 (PGOOD) is zero conditions:

1. B2B SC3(EN1) is zero
2. PROG_B is zero, but B2B nRST_SC0 and B2B SC3(EN1) are set high. In this case PROG_B is not set high with CPLD pullup, so 1.8V is missing on CPLD IO Bank is missing.

Reset

PROG_B is set to zero if SC3(EN1) is zero or nRST_SC0 is zero, otherwise high impedance. Internal Pullup on PROG_B CPLD is enabled.

PUD_C

PUD_C is set to zero. Internal Pullup on power up, see UG570

LED

Green LED D1.

Blink Sequence	Priority	Description
*****	1	B2B Reset is set to low
****000	2	EN1 (power enable) is low
***0000	3	Power problem (use PROG_B pullup to check 1.8V)
**00000	4	INIT_B low (CRC or IDCODE error, see UG570)
*000000	5	Done is low (FPGA not programmed, see UG570)
User Defined	6	XIO is connected to LED

Appx. A: Change History and Legal Notices

Revision Changes

REV01 to REV02

- Add 4x5 Module control IOs
- Rework Power
- Rework LED

Document Change History

To get content of older revision got to "Change History" of this page and select older document revision number.

Date	Document Revision	CPLD Firmware Revision	Supported PCB Revision	Authors	Description
		REV02	REV01, REV02	<div>Error render ing macro 'page- info'</div> <div>Ambig uous metho d</div>	CPLD REV02 finished, Firmware released 2018-06-05

**Error rendering macro
'page-info'**

Ambiguous method
overloading for method
jdk.
proxy244.\$Proxy3589#h
asContentLevelPermissi
on. Cannot resolve
which method to invoke
for [null, class java.lang.
String, class com.
atlassian.confluence.
pages.Page] due to
overlapping prototypes
between: [interface com.
atlassian.confluence.
user.ConfluenceUser,
class java.lang.String,
class com.atlassian.
confluence.core.
ContentEntityObject]
[interface com.atlassian.
user.User, class java.
lang.String, class com.
atlassian.confluence.
core.
ContentEntityObject]

Error rendering macro 'page-info'

Ambiguous method overloading for
method jdk.
proxy244.\$Proxy3589#hasContentLevel
Permission. Cannot resolve which
method to invoke for [null, class java.
lang.String, class com.atlassian.
confluence.pages.Page] due to
overlapping prototypes between:
[interface com.atlassian.confluence.user.
ConfluenceUser, class java.lang.String,
class com.atlassian.confluence.core.
ContentEntityObject] [interface com.
atlassian.user.User, class java.lang.
String, class com.atlassian.confluence.
core.ContentEntityObject]



Unknown macro: 'metadata'

overlo
ading
for
metho
d jdk.
proxy2
44.\$Pr
oxy35
89#ha
sConte
ntLeve
lPermi
ssion.
Canno
t
resolv
e
which
metho
d to
invoke
for
[null,
class
java.
lang.
String,
class
com.
atlassi
an.
conflu
ence.
pages.
Page]
due to
overla
pping
prototy

pes
betwe
en:
[interfa
ce
com.
atlassi
an.
conflu
ence.
user.
Conflu
enceU
ser,
class
java.
lang.
String,
class
com.
atlassi
an.
conflu
ence.
core.
Conte
ntEntit
yObjec
t]
[interfa
ce
com.
atlassi
an.
user.
User,
class
java.
lang.

				<div>String, class com. atlassi an. conflu ence. core. Conte ntEntit yObjec t]</div>	
14 Mar 2018	v.3	REV01	REV01	John Hartfiel	CPLD REV01 , Firmware released 2016- 11-02
2018-03-14	v.1	REV01	REV01	<div><div>Error render ing macro 'page- info'</div><div>Ambig uous metho d overlo ading for metho d jdk. proxy2 44.\$Pr oxy35 89#ha sConte</div></div>	Initial release

ntLeve
IPermi
ssion.
Canno
t
resolv
e
which
metho
d to
invoke
for
[null,
class
java.
lang.
String,
class
com.
atlassi
an.
conflu
ence.
pages.
Page]
due to
overla
pping
prototy
pes
betwe
en:
[interfa
ce
com.
atlassi
an.
conflu
ence.

user.
Conflu
enceU
ser,
class
java.
lang.
String,
class
com.
atlassi
an.
conflu
ence.
core.
Conte
ntEntit
yObjec
t]
[interfa
ce
com.
atlassi
an.
user.
User,
class
java.
lang.
String,
class
com.
atlassi
an.
conflu
ence.
core.
Conte
ntEntit

				<div>yObjectj</div>	
	All			<div>Errorrenderingmacro'page-info' Ambiguousmethod d overflowing for methodjdk. proxy2 44.\$Proxy35 89#hasContentLevel IPermission. Cannot resolve e which method d to invoke for</div>	

[null,
class
java.
lang.
String,
class
com.
atlassi
an.
conflu
ence.
pages.
Page]
due to
overla
pping
prototy
pes
betwe
en:
[interfa
ce
com.
atlassi
an.
conflu
ence.
user.
Conflu
enceU
ser,
class
java.
lang.
String,
class
com.
atlassi
an.

					conflu ence. core. Conte ntEntit yObjec t] [interfa ce com. atlassi an. user. User, class java. lang. String, class com. atlassi an. conflu ence. core. Conte ntEntit yObjec t]
--	--	--	--	--	---

Legal Notices

Data Privacy

Please also note our data protection declaration at <https://www.trenz-electronic.de/en/Data-protection-Privacy>

Document Warranty

The material contained in this document is provided "as is" and is subject to being changed at any time without notice. Trenz Electronic does not warrant the accuracy and completeness of the materials in this document. Further, to the maximum extent permitted by applicable law, Trenz Electronic disclaims all warranties, either express or implied, with regard to this document and any information contained herein, including but not limited to the implied warranties of merchantability, fitness for a particular purpose or non infringement of intellectual property. Trenz Electronic shall not be liable for errors or for incidental or consequential damages in connection with the furnishing, use, or performance of this document or of any information contained herein.

Limitation of Liability

In no event will Trenz Electronic, its suppliers, or other third parties mentioned in this document be liable for any damages whatsoever (including, without limitation, those resulting from lost profits, lost data or business interruption) arising out of the use, inability to use, or the results of use of this document, any documents linked to this document, or the materials or information contained at any or all such documents. If your use of the materials or information from this document results in the need for servicing, repair or correction of equipment or data, you assume all costs thereof.

Copyright Notice

No part of this manual may be reproduced in any form or by any means (including electronic storage and retrieval or translation into a foreign language) without prior agreement and written consent from Trenz Electronic.

Technology Licenses

The hardware / firmware / software described in this document are furnished under a license and may be used /modified / copied only in accordance with the terms of such license.

Environmental Protection

To confront directly with the responsibility toward the environment, the global community and eventually also oneself. Such a resolution should be integral part not only of everybody's life. Also enterprises shall be conscious of their social responsibility and contribute to the preservation of our common living space. That is why Trenz Electronic invests in the protection of our Environment.

REACH, RoHS and WEEE

REACH

Trenz Electronic is a manufacturer and a distributor of electronic products. It is therefore a so called downstream user in the sense of [REACH](#). The products we supply to you are solely non-chemical products (goods). Moreover and under normal and reasonably foreseeable circumstances of application, the goods supplied to you shall not release any substance. For that, Trenz Electronic is obliged to neither register nor to provide safety data sheet. According to present knowledge and to best of our knowledge, no [SVHC \(Substances of Very High Concern\) on the Candidate List](#) are contained in our products. Furthermore, we will immediately and unsolicited inform our customers in compliance with REACH - Article 33 if any substance present in our goods (above a concentration of 0,1 % weight by weight) will be classified as SVHC by the [European Chemicals Agency \(ECHA\)](#).

RoHS

Trenz Electronic GmbH herewith declares that all its products are developed, manufactured and distributed RoHS compliant.

WEEE

Information for users within the European Union in accordance with Directive 2002/96/EC of the European Parliament and of the Council of 27 January 2003 on waste electrical and electronic equipment (WEEE).

Users of electrical and electronic equipment in private households are required not to dispose of waste electrical and electronic equipment as unsorted municipal waste and to collect such waste electrical and electronic equipment separately. By the 13 August 2005, Member States shall have ensured that systems are set up allowing final holders and distributors to return waste electrical and electronic equipment at least free of charge. Member States shall ensure the availability and accessibility of the necessary collection facilities. Separate collection is the precondition to ensure specific treatment and recycling of waste electrical and electronic equipment and is necessary to achieve the chosen level of protection of human health and the environment in the European Union. Consumers have to actively contribute to the success of such collection and the return of waste electrical and electronic equipment. Presence of hazardous substances in electrical and electronic equipment results in potential effects on the environment and human health. The symbol consisting of the crossed-out wheeled bin indicates separate collection for waste electrical and electronic equipment.

Trenz Electronic is registered under WEEE-Reg.-Nr. DE97922676.

Error rendering macro 'page-info'

Ambiguous method overloading for method `jdk.proxy244.$Proxy3589#hasContentLevelPermission`. Cannot resolve which method to invoke for `[null, class java.lang.String, class com.atlassian.confluence.pages.Page]` due to overlapping prototypes between: `[interface com.atlassian.confluence.user.ConfluenceUser, class java.lang.String, class com.atlassian.confluence.core.ContentEntityObject]` `[interface com.atlassian.user.User, class java.lang.String, class com.atlassian.confluence.core.ContentEntityObject]`