

TE0741 CPLD

Overview

Table of contents

Firmware for PCB CPLD with designator U7. CPLD Device in Chain: LCMX02-256HC

- 1 [Overview](#)
- 2 [Product Specification](#)
- 3 [Firmware Revision and supported PCB Revision](#)
- 4 [Table of contents](#)

Firmware Revision and supported PCB Revision

- See Document [Change History](#)
- 3.1 [Revision Changes](#)
 - 3.2 [Legal Notices](#)
 - 3.3 [Data Privacy](#)
 - 3.4 [Document Warranty](#)
 - 3.5 [Environmental Protection](#)
 - 3.6 [RoHS and WEEE](#)

Product Specification

Port Description

Name / opt. VHD Name	Direction	Pin	Pullup/Down	Bank Power	Description
C_LED	out	17	none	3.3V	Green LED D4, blinking pattern according to different states
DONE	in	28	up	3.3V	FPGA Done signal, also connected to green LED D3. Is OFF when FPGA configured.
F_TCK / C_TCK	out	9	none	3.3V	FPGA JTAG
F_TDI / C_TDI	out	21	none	3.3V	FPGA JTAG
F_TDO / C_TDO	in	5	none	3.3V	FPGA JTAG
F_TMS / C_TMS	out	4	none	3.3V	FPGA JTAG
GND		10		3.3V	GND
GND		11		3.3V	GND
GND		12		3.3V	GND
GND		13		3.3V	GND
GND		14		3.3V	connected to GND
JTAGMODE		26		3.3V	Enable JTAG access to CPLD for Firmware update (LOW-'0' : JTAG signals routed to module, HIGH-'1' : CPLD access)

MODE	in	16		3.3V	/ currently_not_used
PG_ALL	in	27	up	3.3V	Power sense from 1V/1.8V/3.3V/3.3VIN
PGOOD	inout	25	up	3.3V	Power Good. Low, if power failed, internal pullup activated
PROG_B	out	23	none	3.3V	FPGA Prog_B
RESIN	in	8	up	3.3V	external reset from B2B
TCK / M_TCK	in	30	none	3.3V	B2B JTAG
TDI / M_TDI	in	32	up	3.3V	B2B JTAG
TDO / M_TDO	out	1	none	3.3V	B2B JTAG
TMS / M_TMS	in	29	up	3.3V	B2B JTAG
XIO	in	20	none	3.3V	FPGA IO from Bank14 H26, Can be used to control LED D4 if no error state occurs

Functional Description

JTAG

JTAG signals routed directly through the CPLD to FPGA. Access between CPLD and FPGA can be multiplexed via JTAGEN (logical one for CPLD, logical zero for FPGA) on JM1-89.

Reset

PROG_B is triggered by RESIN or PG_ALL.

Power

PG_ALL is used to trigger PROG_B Reset in case of power failure. This case is also indicated by the green LED D4.

PGOOD is set low, if PG_ALL failed otherwise high impedance. Internal pullup is activated.

PGOOD can be drive to low from carrier, this will be indicated by LED subsequence only.

LED

LED D4 Green			
Status	Blink Sequence	Priority	Comment
Reset	***** ~3Hz	1	external Reset is set
Power failed	*****000	2	PG_ALL Problem (1.8V or 3.3 V)
PGOOD Low	****0000	3	PGOOD is set low from carrier or the power monitor U11 noticed a power failure
DONE	*0000000	4	Module not programmed

idle	OFF	5	Module ready and programmed. In this case LED D4 can be controlled by FPGA - XIO Signal
------	-----	---	---

Appx. A: Change History and Legal Notices

Revision Changes

CPLD REV2 to REV03

- added JTAG DELAY and Pullmode constraints
- XIO can be used to control LED D4

CPLD REV01 to REV02

- add PGOOD functionality
- new LED status sequence

Document Change History

To get content of older revision got to "Change History" of this page and select older document revision number.

Date	Document Revision	CPLD Firmware Revision	Supported PCB Revision	Authors	Description	Firmware release
		REV03	REV02 - REV05		• Update Document Style Error rendering macro 'page-info' Ambiguous method overloading for method jdk.proxy279.\$Proxy4022#f	
2023-12-13	v.7	REV03	REV02 - REV05	Waldemar Hanemann	• Revision 03	2023-12-13 SC-PGM-(TE0741-005_SC0741-003_20231213.zip)
2018-08-29	v.4	REV02	REV02,REV03	John Hartfiel	• Revision 02 released	2018-08-29 (SC-PGM-TE0741-0203_SC0741-02_20180829.zip)
2028-03-08	v.2	REV01	REV02,REV03	John Hartfiel	• Revision 01	2014-07-02

	All					
--	-----	--	--	--	--	--

Error rendering macro 'page-info'

Ambiguous method overloading for method jdk.proxy279.\$Proxy4022#hasContentLevelPe

Legal Notices

Data Privacy

Please also note our data protection declaration at <https://www.trenz-electronic.de/en/Data-protection-Privacy>

Document Warranty

The material contained in this document is provided "as is" and is subject to being changed at any time without notice. Trenz Electronic does not warrant the accuracy and completeness of the materials in this document. Further, to the maximum extent permitted by applicable law, Trenz Electronic disclaims all warranties, either express or implied, with regard to this document and any information contained herein, including but not limited to the implied warranties of merchantability, fitness for a particular purpose or non infringement of intellectual property. Trenz Electronic shall not be liable for errors or for incidental or consequential damages in connection with the furnishing, use, or performance of this document or of any information contained herein.

Limitation of Liability

In no event will Trenz Electronic, its suppliers, or other third parties mentioned in this document be liable for any damages whatsoever (including, without limitation, those resulting from lost profits, lost data or business interruption) arising out of the use, inability to use, or the results of use of this document, any documents linked to this document, or the materials or information contained at any or all such documents. If your use of the materials or information from this document results in the need for servicing, repair or correction of equipment or data, you assume all costs thereof.

Copyright Notice

No part of this manual may be reproduced in any form or by any means (including electronic storage and retrieval or translation into a foreign language) without prior agreement and written consent from Trenz Electronic.

Technology Licenses

The hardware / firmware / software described in this document are furnished under a license and may be used /modified / copied only in accordance with the terms of such license.

Environmental Protection

To confront directly with the responsibility toward the environment, the global community and eventually also oneself. Such a resolution should be integral part not only of everybody's life. Also enterprises shall be conscious of their social responsibility and contribute to the preservation of our common living space. That is why Trenz Electronic invests in the protection of our Environment.

REACH, RoHS and WEEE

REACH

Trenz Electronic is a manufacturer and a distributor of electronic products. It is therefore a so called downstream user in the sense of [REACH](#). The products we supply to you are solely non-chemical products (goods). Moreover and under normal and reasonably foreseeable circumstances of application, the goods supplied to you shall not release any substance. For that, Trenz Electronic is obliged to neither register nor to provide safety data sheet. According to present knowledge and to best of our knowledge, no [SVHC \(Substances of Very High Concern\) on the Candidate List](#) are contained in our products. Furthermore, we will immediately and unsolicited inform our customers in compliance with REACH - Article 33 if any substance present in our goods (above a concentration of 0,1 % weight by weight) will be classified as SVHC by the [European Chemicals Agency \(ECHA\)](#).

RoHS

Trenz Electronic GmbH herewith declares that all its products are developed, manufactured and distributed RoHS compliant.

WEEE

Information for users within the European Union in accordance with Directive 2002/96/EC of the European Parliament and of the Council of 27 January 2003 on waste electrical and electronic equipment (WEEE).

Users of electrical and electronic equipment in private households are required not to dispose of waste electrical and electronic equipment as unsorted municipal waste and to collect such waste electrical and electronic equipment separately. By the 13 August 2005, Member States shall have ensured that systems are set up allowing final holders and distributors to return waste electrical and electronic equipment at least free of charge. Member States shall ensure the availability and accessibility of the necessary collection facilities. Separate collection is the precondition to ensure specific treatment and recycling of waste electrical and electronic equipment and is necessary to achieve the chosen level of protection of human health and the environment in the European Union. Consumers have to actively contribute to the success of such collection and the return of waste electrical and electronic equipment. Presence of hazardous substances in electrical and electronic equipment results in potential effects on the environment and human health. The symbol consisting of the crossed-out wheeled bin indicates separate collection for waste electrical and electronic equipment.

Trenz Electronic is registered under WEEE-Reg.-Nr. DE97922676.

Error rendering macro 'page-info'

Ambiguous method overloading for method jdk.proxy279.\$Proxy4022#hasContentLevelPermission.
Cannot resolve which method to invoke for [null, class java.lang.String, class com.atlassian.confluence.
pages.Page] due to overlapping prototypes between: [interface com.atlassian.confluence.user.
ConfluenceUser, class java.lang.String, class com.atlassian.confluence.core.ContentEntityObject]
[interface com.atlassian.user.User, class java.lang.String, class com.atlassian.confluence.core.
ContentEntityObject]