

Intel Quartus Prime project generation

This step guides through the tasks which have to be done inside Intel Quartus Prime. As mentioned in page "[Board bring-up overview for TEI0022](#)", this step is for project generation, system setting and output creation. Therefore, the work within this step should be explained in three sections:

- Project Creation
- System Setting
- Output Creation


The section "Project Creation" describes the basic work to create a new project. The second section "System Setting" explains the creation of an HPS instance inside the project. And the third section "Output Creation" shows how to create the result output inside Intel Quartus Prime.

Project Creation


This section guides through the project creation:

- Start Intel Quartus Prime
- Select: **File New Project Wizard...**


Now, the following figure should be visible:



- Click **Next >**
- Select the project folder and the project name (e.g. HPSEXample). Then, click **Next >**
- Select an "Empty project" and click **Next >** in the window "Project Type"
- Click **Next >** in the window "Add Files"
- Select the used FPGA in the window "Family, Device & Board Settings". For the board TEI0022, copy "5CSEMA5F31C8(N)" into the field "Name filter", select the "5CSEMA5F31C8(N)" SoC and click **Next >**.




- Click **Next >** in the window "EDA Tool Settings"
- Click **Finish** in the window "Summary"
- The Intel Quartus project is generated and the folder should look like the next figure.




System Setting

This section guides through the system setting with the Platform Designer to generate and configure the HPS according to the physical board resources.

- Create a Platform Designer file: **File > New**
- Select **"Qsys System File"** and press **"OK"**
- A new window should open.
- Look for **"hps"** inside the search field, as visible in the following figure.



- Select "Arria V/Cyclone V Hard Processor System" via double click from the tree: **Library Processors and Peripherals Hard Processor Systems Arria V/Cyclone V Hard Processor System**
- The window "Arria V/Cyclone V Hard Processor System - hps_0" should be opened as visible in the next figure.




- In this window the HPS has to be configured with the following settings:
 - Tab FPGA Interface:
 - Uncheck "Enable MPU standby and event signals" (default)
 - AXI Bridges:
 - FPGA-to-HPS interface width: **Unused**
 - HPS-to-FPGA interface width: **Unused**
 - Lightweight HPS-to-FPGA interface width: **Unused**
 - Tab Peripheral Pins:
 - Quad SPI Flash Controller
 - QSPI pin: **HPS I/O Set 0**
 - SD/MMC Controller
 - SDIO pin: **HPS I/O Set 0**
 - SDIO mode: **4-bit Data**
 - UART Controllers

- UART0 pin: **HPS I/O Set 0**
 - UART0 mode: **no Flow Control**
 - I2C Controllers
 - I2C0 pin: **HPS I/O Set 1**
 - I2C1 pin: **HPS I/O Set 0**
 - Tab HPS Clocks:
 - As is / Accept the default values (for both subtabs)
 - Tab SDRAM
 - Subtab Phy Settings:
 - Memory clock frequency: **333.3 MHz**
 - PLL reference clock frequency: **25 MHz**
 - Subtab - Memory Parameters:
 - Memory device speed grade: **800.0 MHz**
 - Total interface width: **32**
 - Row Address width: **16**
 - Column Address width: **10**
 - Memory Initialization Options
 - Memory CAS latency setting: **5**
 - ODT Rtt nominal value: **RZQ/6**
 - Memory write CAS latency settings: **5**
 - Subtab - Memory Timing:
 - tIS (base): **180 ps**
 - tIH (base): **140 ps**
 - tDS (base): **30 ps**
 - tDH (base): **65 ps**
 - tDQSQ: **100 ps**
 - tQH: **0.38 cycles**
 - tDQSCK: **225 ps**
 - tDQSS: **0.27 cycles**
 - tQSH: **0.4 cycles**
 - tDSH: **0.18 cycles**
 - tDSS: **0.18 cycles**
 - tINIT: **500 us**
 - tMRD (tMRW): **4 cycles**
 - tRAS: **35.0 ns**
 - tRCD: **13.75 ns**
 - tRP: **13.75 ns**
 - tREFI (tREFIab): **7.8 us**
 - tRFC (tRFCab): **350.0 ns**
 - tWR: **15.0 ns**
 - tWTR: **4 cycles**
 - tFAW: **40 ns**
 - tRRD: **12.0 ns**
 - tRTP: **12.0 ns**
 - Subtab - Board Settings:
 - Board Skews
 - Maximum CK delay to DIMM/device: **0.03**
 - Maximum DQS delay to DIMM/device: **0.02**
 - Minimum delay difference between CK and DQS: **0.09**
 - Maximum delay difference between CK and DQS: **0.16**
 - Maximum skew within DQS group: **0.01**
 - Maximum skew between DQS groups: **0.08**
 - Maximum skew within address and command bus: **0.03**
- Click "**Finish**" to close the window "Arria V/Cyclone V Hard Processor System - hps_0".
 - Add connections via clicking into the circle marked with a red rectangle in the next figure:
 - hps_0 - h2f_reset clk_0 - clk_in_reset
 - clk_0 - clk hps_0 - f2h_sdram0_data


Use	Connections	Name	Description	Export	Clock
☒		clk_0 clk_in clk_in_reset clk clk_reset hps_0 h2f_mpu_events memory hps_io h2f_reset f2h_sdr0m0_clock f2h_sdr0m0_data	Clock Source Clock Input Reset Input Clock Output Reset Output Arria V/Cyclone V Hard Processor System Conduit Conduit Conduit Reset Output Clock Input AXI Slave	clk Double-click to export Double-click to export Double-click to export Double-click to export Double-click to export memory hps_io Double-click to export Double-click to export Double-click to export	exported clk_0 clk_0 f2h_sdr0m0_data

IP cores top entry


- The HPS is nearly configured. Apply some auto functions:
 - System Assign Base Addresses
 - System Assign Interrupt Numbers
 - System Assign Custom Instruction Opcodes
 - System Create Global Reset Network
- Click **Generate HDL...** to generate the hardware description language file.
- Window "Generation" opens.
- In this window, under "Synthesis", select via dropdown menu in which Hardware Language your HDL will be created, **Verilog** or **VHDL**.
- Uncheck **Create timing and resource estimate...**
- Check **Create block symbol file (.bsf)**.
- Click **Generate**, as visible in the next figure.




- Save** the changes according to the opened saving dialogue, which is shown in the next figure.




- Name the file (e.g. **PlatformEditorHPS.qsys**) and press **Save**, as visible in the next figure.




- After saving, the message "Save System: Completed successfully." should be shown and the view should be similar to the next figure.



- Press **Close**.
- Wait until the generation is finished and the message "Generation: Completed successfully." is shown according to the next figure.



- Press **Close**.
- Leave the Platform Designer by pressing **Finish**.
- A notification appears, reminding to add files into the project, press **OK**.




Close the **Platform Designer** by pressing **Finish**.


Output Creation

This section guides through the output creation:

- Add the file "**PlatformEditorHPS.qsys**" to the project by using **Project Add/Remove Files in Project ...**
- Click onto the button with three dots (inside the red rectangle) in the opened window as visible in the next figure.



- In the "Select File" window select the file ... > **PlatformEditorHPS synthesis PlatformEditorHPS.qip**.
- Click **OK**.
- Change the view from "Hierarchy" to "Files" inside the drop-down menu withing the "Project Navigator".
- Set file "PlatformEditorHPS.qip" as top-level entity by right clicking onto the file and selecting **Set as Top-Level Entity**.
- Select **Tools Tcl Scripts...**
- Select **Project PlatformEditorHPS synthesis submodules hps_sdram_p0_pin_assignments.tcl** and click **Run**.
- Confirm the notification and close the previous window through **Close**.
- Press **Processing Start Compilation**
- Compilation process has to be finished without errors. Fix errors if there are some.
- The project folder should look like the following figure.



After this doing this guide, following files and folders are generated with the given purpose which are relevant for the next guide.

File/Folder	Purpose
.sopcinfo	SOPC Info File containing hardware description for the Device Tree Generator
hps_isw_handoff	Folder containing a hardware description for the Preloader Generator